

Outback – MidNight E-Panel

MNE-125AL-L

The MidNite Solar E-Panel comes standard with the basic over-current protection and disconnects required to install your renewable energy system. It can also expand to grow as your needs arise.

Inverter installation has just gone from hours to minutes with MidNite Solar's E-Panel. These disconnect boxes can easily be stacked horizontally or vertically to save space

Breaker: 125 Amp 125 VDC

Material: White Aluminum

Hinge Side: Left Side Hinge

Dimensions: 14" X 12" X 28"

Weight: 19 Lbs



Features

- * Small size compared to existing disconnect and over current solution
- * Pre-wired to save time, money and complexity. All field wiring connections clearly labeled
- * White powder coated aluminum
- * Easily expands to accommodate additional inverters
- * Six slots for din rail breakers, PV, Wind, Hydro, AC distribution
- * Pre-wired 50 amp 240VAC rated Inverter AC bypass switch
- * Pre-wired 50 amp 240VAC rated AC Input disconnect
- * Bus bars for Battery Plus, Battery Minus and ground
- * Mounting hardware for Inverter and charge controller
- * Mounting brackets for hanging E-Panel on wall
- * Heavy duty 175 amp AC distribution block
- * ETL listed to UL and Canadian standards
- * Left hand hinged door to mount inverter
- * Knockouts for AC and DC conduits
- * Charge control bracket (CCB)
- * Cut outs for two GFCI outlets
- * DC Inverter battery breaker
- * Internal inverter cables

"bringing renewable
& efficient alternatives
to home environments"

BREATHE
S Y S T E M S®

www.breathesystems.com

Switzerland +41 44 586 77 00 | UK +44 121 288 8383 | USA +1 646 217 0888 | Hong Kong +852 8197 2777 | Australia +61 7 3103 3357